

24V/49AH Outdoor Portable Power Station User Manual



summary

24V 49Ah battery

p. 03

Battery charging settings

p. 04

general characteristics of the BMS

p. 03

Precautions

p. 05

Waterproof to charge the battery

p. 03

24V 49Ah battery

Our 24V 49Ah battery is designed for small power banks.

BMS of the general characteristics

A battery management system (BMS) is designed to monitor the battery's charge, current, and temperature. When the BMS detects that the battery or cell exceeds the programmed threshold, the battery will enter the "Protection" state. In this state, the outer battery terminals are disconnected from the internal battery cell.

High Voltage Protection:

If the voltage of a single battery exceeds a specified threshold during charging, **BMS** will prevent the charging current from continuing. Discharge is still allowed in this case.

Low voltage protection:

If a single battery falls below a specified threshold during discharge, **BMS** Further discharges will be prevented. Although the battery is in "low voltage disconnect" mode, charging is still allowed in this state. The voltage on the outer positive terminal of a battery that is disconnected at low voltage is zero. Many chargers must detect voltages greater than 19.2V in order to charge the battery.

High Temperature Protection:* (65°C during charge and discharge)

When discharging, if the battery temperature exceeds 65°C, the battery BMS will enter protection mode. It will not allow for discharge currents. When charging, if the battery temperature exceeds 60°C, the battery BMS will enter protection mode. It does not allow charging current.

Low Temperature Protection: (-40°C | -40°C when charging)

During discharge, if the battery temperature is lower than -40°C, the battery BMS will enter protection mode. It will not allow for discharge currents. When charging, if the battery temperature is lower than -40°C, the battery BMS will enter protection mode. It does not allow charging current.

High charge/discharge current protection

BMS It is not allowed to charge or discharge the current beyond the threshold specified by the BMS board. For specific details on current thresholds, please refer to the battery datasheet.

Parallel

Batteries can be connected in parallel to increase the ampere-hour capacity of the system (we recommend using a busbar to interconnect the battery with the rest of the system.) The busbar must be able to withstand the DC capacity of all the batteries combined). When the cells are connected in parallel, the system voltage does not change, but the DC and ampere-hour values are added together. Therefore, all cables and connections must be able to handle the high currents provided by the battery. Proper fuses and circuit breakers are also required to protect all components from current spikes and short circuits. Batteries connected in parallel must be in the same state of charge (same voltage) before they can be connected.

To avoid excessive discharge currents from one battery to another, use a suitable lithium titanate battery charger to charge each set of batteries to ensure that they are all in the same state of charge or voltage.

Watertight

The battery is IP65 rated. It is equipped with a sheet metal case, outdoor protective spraying, which helps to maintain the waterproofness of the battery. It must be installed properly to avoid infiltration. Please note that there is still a sealant (epoxy/silicone) inside the connector to provide a safety barrier, but external protection is still essential and mandatory to maintain the warranty.

If the battery is installed in a humid environment where condensation may form, or where the battery may get wet with rain, it is best to prevent the battery from excessive exposure to water for long periods of time.

Charge the battery :

You can charge the lithium titanate battery after each use or after discharging to 20% (state of charge). If the BMS disconnects the battery due to low voltage (0% state of charge), charge it immediately.

For the first use, it is recommended to charge this product until it is fully charged.

Connect the positive wire of the load to the positive pole (red) of the product, and the negative wire to the negative pole (black) of the product and fasten it with screws to charge the product.

Battery charging settings

The following are the general charging parameters of 24V lithium battery :

Charging parameters 24V	Discharging voltage parameters 24V
Overcharge voltage: 28– 28.5V	Low voltage cut-off 19.2V
Absorption voltage : 28 –28.5V	High voltage cut-off 30V
Charging time: 0-60 minutes	
The float charge voltage is 28.5V	

The following is the interface description of the 24V lithium battery outdoor power station :



Reserve

When the product is stored for a long time and not in use, please place it in a dry and ventilated place to avoid flammable and explosive materials; Charge and maintain the battery pack regularly every three months to ensure that the battery is in an optimal performance state.

Precautions

Do not dispose of this product in water.

It is forbidden to charge and use this product outside the temperature range specified by our company; Do not store, charge or use this product near fire or heat sources.

- 1) When this product emits peculiar smell or leaks, stop using or charging immediately, and move to an open and ventilated place, away from the fire source, and contact our company in time.
- 2) This product cannot be used in series or parallel. When the load is turned on, do not reverse the positive and negative poles.
- 3) Do not use metal conductors to short-circuit the positive and negative electrodes of this product.
- 4) Do not dispose of this product in fire or artificial heating.
- 5) It is strictly forbidden to artificially disassemble this product, it is strictly forbidden to pierce this product with nails or sharp objects, and it is strictly forbidden to hit this product with a hammer or other external force. This product is trampled and dropped by man.
- 8) It is strictly forbidden to put this product in a microwave oven or pressure vessel.
- 9) If there is any abnormal phenomenon during charging or use, please stop charging and using it immediately.
- 10) The optimal operating temperature for this product is $22\pm 5^{\circ}\text{C}$, and if the product is not within this temperature range during use, the discharge capacity will be reduced.
- 11) If there is a failure or abnormality during use, please contact our company, please do not disassemble this product without permission.
- 12) When it is not used for a long time in 3~6 months or overused (discharged) to the power is too low, the product will enter sleep, and the subsequent normal use must be woken up and replenished first.
- 13) Wake-up Processing: Charge to wake up.
- 14) The 24V battery of this product supports the use of 220V normal mains electrical appliances.
- 15) The charging limit voltage of this product is less than 30V.
- 16) Do not connect the main switch harness with other wiring harnesses, the main switch wiring harness is the high-voltage part of the battery.
- 17) External harness wiring is defined by labels.